

Description

- **8** sockets controlled independently via Ethernet/Internet with the web browser.
- Worldwide control.
- No software (except web browser) needed to control or adjust.
- Can be used by any operating system (with a web browser).
- **HTML of the pages can be changed** and loaded on.
- **8 inputs or outputs** (IO) - freely configurable with edge detection and toggle (not ADV).
- Plain text **backup system**. Settings can be changed and loaded.
- **Sensor** (temperature, humidity and brightness) connectable (only HUT, HUT2).
- Automatic IP assignment: DHCP.
- Automatic time setting from an SNTP server.
- Calling via host name eg: http: // net-control or IP.
- Free choice of the HTTP port (0-65535), thus several devices accessible from the Internet.
- **'HoldOn'** buttons: relay or IO remains on as long as the button is held down. Two relays or IO's can be used for the +/- control (for example dimmer).
- 30 plain text **timers** for relays & IO with "If timer" (switches depending on the relay or IO).
- **Timer Exceptions** (day / month). On selected days all timers are skipped.
- **Keepalive function**: A network device can be pinged and - should it not respond - be disconnected from the mains for an adjustable period of time.
- Automatic and time-delayed (0-18.2h) switching on the sockets after starting (power failure).
- Switching can also be done as a pulse (0-65535 sec.; 0-18.2h).
- Time distance of the relays with simultaneous switching can be determined.
- **Wake on LAN**.
- Sockets can be locked individually.
- **User system** with rights assignment.
- German / English selectable as menu language.
- **Logbook** of the last 128 events. Power failures are registered (**retained without voltage**).
- **UDP interface and URL interface** for integration into own software.
- Multi NET-PwrCtrl Controls all devices on the network (also as **C# source code**).
- Firmware upgrade via Ethernet possible at any time (Ethernet Bootloader).

LAN interface

Standards Compliance
Data transfer rates
Protocols

Plug type
Cable Compatibility

IEEE802.3(10 Base-T)
10 MBit/s
ARP, DNS, IP, NetBIOS Name Service, ICMP (Ping), UDP, TCP,
DHCP, HTTP, SNTP, SMTP.
RJ-45
100 BASE-TX: Category 5, 2 4 UTP 10
BASE-T: Category 3, 4, 5 2 UTP

ADV

Characteristics:

Sockets (Controllable):
Digital input / output (I / O):
Nominal voltage:
LAN cable
Power cable
Power consumption

Max. Load on the sockets
All total max .:
Each socket max .:

ADV - PRO

8 (8)
no
100-240VAC 50-60Hz
2 m
1,9 m
3,6 W

2300 VA
2300 VA

ADV- POWER

8 (8)
no
100-240VAC 50-60Hz
2 m
1,9 m
3,6 W

4600 VA
2300 VA

ADV - POWER 19"

8 (8)
no
100-240VAC 50-60Hz
2 m
1,9 m
3,6 W

4600 VA
2300 VA

IO

Characteristics:

Sockets (Controllable):
Digital input / output (I / O):
Nominal voltage:
LAN cable
Power cable
Power consumption

Max. Load on the sockets
All total max .:
Each socket max .:

IO - PRO

8 (8)
8 x DB15 Socket
100-240VAC 50-60Hz
2 m
1,9 m
3,6 W

2300 VA
2300 VA

IO- POWER

8 (8)
8 x DB15 Socket
100-240VAC 50-60Hz
2 m
1,9 m
3,6 W

4600 VA
2300 VA

IO - POWER 19"

8 (8)
8 x DB15 Socket
100-240VAC 50-60Hz
2 m
1,9 m
3,6 W

4600 VA
2300 VA

HUT 2

Characteristics:

Relays
Digital input/output (I/O):
Sensor Port
Nominal voltage:
LAN cable
Power consumption

Max. Load of a relay

HUT2(C) LV(-S)

8
8
RJ45
8-30VAC/10-40VDC
2 m
1,6 W

16A/250V~ 16A/14V-
TÜV R50126372

HUT2(C) HV(-S)

8
8
RJ45
100-240VAC 50-60Hz
2 m
3,6 W

16A/250V~ 16A/14V-
TÜV R50126372

HUT 3

Characteristics:

Relays
Digital input/output (I/O):
Sensor Port
Nominal voltage:
LAN cable
Power consumption

Max. Load of a relay
HUT3-T: Max. Load on a transistor (only
transistor mode)

HUT3(-T) LV

8
8
RJ45
8-30VAC/10-40VDC
2 m
1,6 W

16A/250V~ 16A/14V-
200VA max. 300VAC/VDC

HUT3(-T) HV

8
8
RJ45
100-240VAC 50-60Hz
2 m
3,6 W

16A/250V~ 16A/14V-
200VA max. 300VAC/VDC

Installation

Connect the network cable. Connect the NET-PwrCtrl to the mains.
The LED flashes fast in the first 2 seconds and then every second.
Since most networks have a DHCP server (also present in a DSL-Router), the network setting is automated.

Start the browser with the address: <http://net-control> or net-control/.

User: **admin**
Password: **anel**

If the device does not answer, please check if the DHCP server is present in the network or continue with the instructions "Without DHCP" below.

The program [,NET-PwrCtrl Discoverer.exe](#) searches for all devices in the network.

With DHCP

Since most networks have a DHCP server (also present in a DSL-Router), the network setting is automated. After switching on the NET-PwrCtrl, the DHCP function ensures the allocation of all necessary parameters to be included in the network.

The device can now be accessed via browser with the address: <http://net-control>.

Without DHCP (not recommended)

Connect the device and assign the following parameters to the network card:

IP: 192.168.0.1;
Subnet mask: 255.255.255.0.

The device can now via browser with the address:
<http://192.168.0.244>
or
<http://net-control>
be called and adjusted as desired.


ADV, IO



Ethernet jack:
Green LED = Ethernet connected
Orange LED = Data transmission

Fuse 10A + spare fuse

HUT 2



Call NET-PwrCtrl

Call the NET-PwrCtrl:

- About the hostname from the browser. Name of the device = hostname. (http://net-control in delivery state). If the name of the device is changed, the host name changes accordingly.
- About ,[NET-PwrCtrl Discoverer.exe](#)'. This program searches for all devices in the network and lists them. Double-click on the found strip opens it in the browser.
- Over IP, for example: 192.168.0.5. The IP address is from the DHCP server (mostly in the router) automatically assigned. If the DHCP server is missing, the IP can also be assigned manually.

Multiple devices in the network: The NET-PwrCtrl is supplied with the host name: "net-control". The host name must be unique on the network, so it must be changed in the first NET-PwrCtrl before the second one can be connected.

HTTP Port: If default port HTTP 80 has been changed to address multiple devices from the Internet or to operate HTTP server, address the device have to specify the hostname (or IP) + ":" + port number, e.g. http://net-control:85.

Two same host names with different IP's in the router table may disturb the connection until prevented.

Reset

Reset the NET-PwrCtrl: via Settings/LAN/Factory Settings

or reset button:

Press and hold the reset button for more than 4 seconds. The power LED will flash 2 times per second. Release the button.

For settings: Time, I/O, Switching, Wake On LAN, Timer, Keepalive and Sensors can be clicking on the star (top right)  reset **this single function** to factory settings.

Display (only HUT3)

Pressing the reset button once switches the display on. Pressing again switches between displays. The status of the reset button is shown in the display: restart / reset / cancel

Restart: Hold the reset button down for > 4 seconds. The power LED then flashes twice per second. The display shows: "Restart". Release the button. Device restarts.

Factory settings: Hold the reset button down for > 8 seconds. The power LED then flashes 4 times per second. Display shows: "Reset". Release the button. NET-PwrCtrl is reset and restarts.

If you continue to hold the reset button, "Cancel" appears. After releasing the button, the device continues to work without any changes. Reset process is canceled.

HTML-Upload

The HTML of the pages can be changed and uploaded.

Please note:



There are max. 256kB Flash memory for HTML available.
File name can not be longer than 20 characters (including extension).

Important! If NET-PwrCtrl can not be reached after the upload (error in the HTML data), via `/html_upload` a direct connection to the upload can be established.

The HTML data (HTML/webpages) can be merged with the *HTTP Image Builder.exe* into a .bin file (HTML_Img.bin). This .bin file can be then uploaded. Depending on the size of the .bin file, the process takes up to 30 seconds.

If there are problems with the display in the browser:
Delete browser data (history) (Ctrl + Shift + Del)

HTTP Image Builder.exe



Files that are in the * .bin file to be compiled.

Files that do not contain ~name~ variables are compressed. Specify data types that should not be compressed here.

Control

Relays/Sockets

Name / Position / Function

Temperature inside.

Relay / Sockets

Control

NET - Power Control 192.168.2.109 28.8°C

Relays

Server #1 ①	Licht ②	Mikroskop ③	Nr.4 ④
Nr.5 ⑤	Nr.6 ⑥	Nr.7 ⑦	Nr.8 ⑧

HoldOn

Blocked

Control

Sockets/Relays

Green	= switched on
Brown	= switched off
Blue	= switched on HoldOn
Dark blue	= switched off HoldOn
Light green	= blocked switched on
Light Brown	= blocked switched off
Frame white	= Blinking

IO = Switched by IO

W = Wait for switching

K = Keepalive is on

B = Blinking is on

P = Impulse is on

S = Switched by Sensor

Digital Input/Output (I/O) This feature is not in ADV

IO In-/Output

Input / Output

IO-1 ①	IO-2 ②	IO-3 ③	IO-4 ④
IO-5 ⑤	IO-6 ⑥	IO-7 ⑦	IO-8 ⑧

Output

input

IO Input/Output

Output

Green	= switched on
Brown	= switched off
Blue	= switched on HoldOn
Dark blue	= switched off HoldOn
Frame white	= Blinking

Input

Light green	= '1'
Light Brown	= '0'

LAN

Hostname = name of the device must be unique in the network.

Network Settings

Hostname

NET-CONTROL

no special characters or spaces

Automatic IP setting

S-Nr. 880518 made 5.2018

☒ DHCP

(for a static IP switch DHCP off)

TCP/IP Settings

These parameters are assigned by DHCP.

IP:

192.168.2.109

Mask:

255.255.255.0

Gateway:

192.168.2.1

First DNS:

192.168.2.1

Second DNS:

0.0.0.0

MAC:

00:04:A3:12:05:58

If default port HTTP 80 has be changed to address multiple devices from the Internet or to operate HTTP server, address the device have to specify the hostname (or IP) + ":" + port number, e.g. http://net-control:85.

HTTP Port

80

0-65535

The MAC can not be changed.

☒ Allow UDP communication

Send

77

(port number)

0-65535

Receive

75

After saving the device restarts!

After IP - change we recommend to turn device off and on.

Restart

Factory Settings

Upload HTML

Firmware Update

Save

MAC must be unique in the network and must not be changed. The last three pairs of digits form the serial number.

The **UDP communication**. The UDP interface can also be used to control the device from its own application.

Factory settings: Sets all parameters of the device to factory settings and restarts without changing the switching status of the relays.

The functions: Save, Restart, Factory Settings and Firmware Update restarts NET-PwrCtrl.

Important: If the host name or IP of the device has been changed:

- Browser (all windows) must be closed.
- Start the browser and call NET-PwrCtrl with the host name.

After 6 minutes, the assignment in the browser / NetBios will be deleted automatically.

User

Username and password are limited to 12 characters each. Options without permission are not displayed. This setting is also relevant for the UDP control (user;password).

Authentication (Login) can be switched off here. This option only appears when admin is logging in.

The language can be changed here anytime. After saving, the browser is automatically refreshed.

☐ without authentication / login

User name	Password	Admin	Permission
1 admin	English ▼	<p>After changing the language Browser will be refreshed.</p> <p>All options allowed.</p> <p><input checked="" type="checkbox"/> Control <input type="checkbox"/> Lan <input type="checkbox"/> User <input type="checkbox"/> Time <input type="checkbox"/> E-Mail <input type="checkbox"/> I/O <input type="checkbox"/> Switching</p> <p><input type="checkbox"/> Hybrid <input type="checkbox"/> WOL <input type="checkbox"/> Timer <input type="checkbox"/> Keepalive <input type="checkbox"/> Sensors <input type="checkbox"/> Backup <input checked="" type="checkbox"/> Logbook</p> <p>Relays: <input checked="" type="checkbox"/> 1 <input checked="" type="checkbox"/> 2 <input checked="" type="checkbox"/> 3 <input checked="" type="checkbox"/> 4 <input checked="" type="checkbox"/> 5 <input checked="" type="checkbox"/> 6 <input checked="" type="checkbox"/> 7 <input checked="" type="checkbox"/> 8 Deutsch ▼</p>
2 user1		<p><input checked="" type="checkbox"/> Control <input type="checkbox"/> Lan <input type="checkbox"/> User <input type="checkbox"/> Time <input type="checkbox"/> E-Mail <input type="checkbox"/> I/O <input type="checkbox"/> Switching</p> <p><input type="checkbox"/> Hybrid <input type="checkbox"/> WOL <input type="checkbox"/> Timer <input type="checkbox"/> Keepalive <input type="checkbox"/> Sensors <input type="checkbox"/> Backup <input checked="" type="checkbox"/> Logbook</p> <p>Relays: <input checked="" type="checkbox"/> 1 <input checked="" type="checkbox"/> 2 <input checked="" type="checkbox"/> 3 <input checked="" type="checkbox"/> 4 <input checked="" type="checkbox"/> 5 <input checked="" type="checkbox"/> 6 <input checked="" type="checkbox"/> 7 <input checked="" type="checkbox"/> 8 Deutsch ▼</p>
3 user2		<p><input checked="" type="checkbox"/> Control <input type="checkbox"/> Lan <input type="checkbox"/> User <input type="checkbox"/> Time <input type="checkbox"/> E-Mail <input type="checkbox"/> I/O <input type="checkbox"/> Switching</p> <p><input type="checkbox"/> Hybrid <input type="checkbox"/> WOL <input type="checkbox"/> Timer <input type="checkbox"/> Keepalive <input type="checkbox"/> Sensors <input type="checkbox"/> Backup <input checked="" type="checkbox"/> Logbook</p> <p>Relays: <input checked="" type="checkbox"/> 1 <input checked="" type="checkbox"/> 2 <input checked="" type="checkbox"/> 3 <input checked="" type="checkbox"/> 4 <input checked="" type="checkbox"/> 5 <input checked="" type="checkbox"/> 6 <input checked="" type="checkbox"/> 7 <input checked="" type="checkbox"/> 8 Deutsch ▼</p>
4 user3		<p><input checked="" type="checkbox"/> Control <input type="checkbox"/> Lan <input type="checkbox"/> User <input type="checkbox"/> Time <input type="checkbox"/> E-Mail <input type="checkbox"/> I/O <input type="checkbox"/> Switching</p> <p><input type="checkbox"/> Hybrid <input type="checkbox"/> WOL <input type="checkbox"/> Timer <input type="checkbox"/> Keepalive <input type="checkbox"/> Sensors <input type="checkbox"/> Backup <input checked="" type="checkbox"/> Logbook</p> <p>Relays: <input checked="" type="checkbox"/> 1 <input checked="" type="checkbox"/> 2 <input checked="" type="checkbox"/> 3 <input checked="" type="checkbox"/> 4 <input checked="" type="checkbox"/> 5 <input checked="" type="checkbox"/> 6 <input checked="" type="checkbox"/> 7 <input checked="" type="checkbox"/> 8 Deutsch ▼</p>

Relays/sockets can be disabled for users and displayed as inactive (as locked in Settings/Switching).

Login

Own (encrypted) login system with session management for up to 3 users. It can be logged out manually or automatically with the session timer. A secure connection from the internet was the main goal (if VPN setup should not be possible).

After logging in, working with the NET-PwrCtrl can end in two ways:

- 1. Close browser window. The device can be called up - without login - until the session timer has expired.
- 2. End session (logout). In the top left of the NET-PwrCtrl window click on 'Logout'. It must be logged in again the next time it is called up.

The session time does not count as long as the browser window is open.

When calling from the non-private IP area (private IP = 10.0.0.0-10.255.255.255, 172.16.0.0- 172.31.255.255, 192.168.0.0-192.168.255.255), we always **recommend logging out**. After closing the window (without logout) the session will be closed after a maximum of 20 seconds.

User login session (only visible by admin).

Session holding. After closing the window and after 20-65535 seconds have elapsed, the user is automatically logged out. Access from the Internet (external) is logged out after a maximum of 20 seconds after the window is closed.

600 = 00:10:00

IP	MAC	Session Timer (hh:mm:ss)	User
192.168.188.30	FC:AA:14:0D:8E:C9	00:10:00	1

Save

Time

With Internet access, the time is automatically synchronized by an SNTP server (port 123 - must not be blocked by the firewall). The system clock is corrected every 4 hours with the SNTP time. Without Internet access, the time must be synchronized via browser time / system time.

The timers are inactive without valid time synchronization.

Time Setting

with the Internet time server (SNTP port 123):

The time is synchronized automatically (every 60 min.) with the Internet Time Server (SNTP). Port 123 should not be blocked. After the restart/power-failure the clock is synchronized immediately.

Permit	SNTP Server:	DST correction
<input checked="" type="checkbox"/>	<input type="text" value="de.pool.ntp.org"/>	<input checked="" type="checkbox"/> It's summertime

Internal clock: Fri 10/08/2018, 15:39:23

SNTP test

To calculate the sunrise and sunset, specify latitude in the format B ± 90,0 °. Southern latitude is indicated by "-". Specify latitude in the format: L ± 180,0 °. Western length is indicated by "-". To the geographical position the time zone (UTC) have to be changed. In DST time 1 hour is added. With the correction, the on and off times can be adjusted. The respective sunrise and sunset times will be recalculated every day at midnight.

Sunrise and sunset

To calculate the sunrise and sunset: specify time zone according to UTC, latitude and longitude. Latitude in the format: ± 90.0°. South latitude with minus in the front. Longitude in the format: ± 180.0°. West longitude with minus in front. In the summer time 1 hour will be added.

Time zone	Geo. location	LAT±90,0°	LONG±180,0°	Calculated	Correction ±120	Timer-time
<input type="text" value="1"/>	latitude	<input type="text" value="51.55"/>	<input type="text" value="+north"/> <input type="text" value="-south"/>	sunrise: 06:13	+ <input type="text" value="-60"/> min. =	05:13
UTC ±12	longitude	<input type="text" value="6.76"/>	<input type="text" value="+east"/> <input type="text" value="-west"/>	sunset: 21:02	+ <input type="text" value="60"/> min. =	22:02

Save

If Internet access is not possible, the internal clock of the device must be synchronized via the system clock (computer time).

synchronize with browser time:

If Internet access is not possible, the internal clock must be synchronized with system (computer time). The automatic synchronization in this mode is not possible. It is important (after a power failure) to make manually synchronization because the timers can not work without clock.

System time: Fri, 10/08/2018, 15:39:19

Set the clock

E-Mail

Events in the NET-PwrCtrl can be reported by e-mail. Max. 10 messages will be collected or sent after 10 sec. The emails are numbered bottom right.

E-Mail Notification ★

Events in the NET-PwrCtrl can be reported by e-mail. Max. 10 messages will be collected or sent after 10 sec. The emails are numbered bottom right. The e-mail language is the admin language.

☒ **Send e-mail** ☐ without logbook entry.

E-Mail settings

at: e-mail address

cc: e-mail address

from: e-mail address

Subject:

Message:

E-Mail No: 13

Test
Save

Example E-Mail

Es ist ein Test...							
Host		IP	Function / name				
NET-TEST		192.168.188.43	NET - Power Control				
(New)Start on:		Firmware Version	Temperature (inside)				
23.03.2019 - 21:03:39		6.5	23.1 °C				
Sensor							
Temperature		Humidity	Brightness				
20.11 °C		43.2 %	0 lx				
Relays							
Nr.1	1	Nr.2	2	Nr.3	3	Nr.4	4
Nr.5	5	Nr.6	6	Nr.7	7	Nr.8	8
Logbook entry (last event above)							
Date		Relays		Event		IP	
26.03.19 18:05:10				Setting changed		192.168.188.27	
E-Mail No.: 184							

IO - Input/Output

This feature is not in ADV

IO can be used as an input - to recognize external events such as: doors, windows, etc;
as output - further control channels can be set up.

The purpose of the inversion is - regardless of the type of switching (normally open or normally closed) - to represent all desired keys the same. Example: If IO1 - IO3 normally-open and IO4 normally closed, IO4 can be inverted so that all inputs are displayed identically and therefore changes are detected more quickly.

A pullup resistor "pulls" the input to logical 1 (about 2.5V). This allows switches - connected between GND and an input - to be operated directly (without additional elements).

Settings I/O

☒ IO switch on
 ☐ Switch IO Pull Up Resistor

No.	Name	Output	Input	Invers	Hold On	Symbol	Control					Switch relay(s) thru I/O:							
							H	LH	HL	TL	TH	1	2	3	4	5	6	7	8
1	IO-1	<input checked="" type="radio"/>	<input type="radio"/>	<input type="checkbox"/>	<input type="checkbox"/>	10112	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	
2	IO-2	<input checked="" type="radio"/>	<input type="radio"/>	<input type="checkbox"/>	<input type="checkbox"/>	10113	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	
3	IO-3	<input checked="" type="radio"/>	<input type="radio"/>	<input type="checkbox"/>	<input type="checkbox"/>	10114	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	
4	IO-4	<input checked="" type="radio"/>	<input type="radio"/>	<input type="checkbox"/>	<input type="checkbox"/>	10115	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	
5	IO-5	<input checked="" type="radio"/>	<input type="radio"/>	<input type="checkbox"/>	<input type="checkbox"/>	10116	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	
6	IO-6	<input checked="" type="radio"/>	<input type="radio"/>	<input type="checkbox"/>	<input type="checkbox"/>	10117	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	
7	IO-7	<input checked="" type="radio"/>	<input type="radio"/>	<input type="checkbox"/>	<input type="checkbox"/>	10118	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	
8	IO-8	<input type="radio"/>	<input checked="" type="radio"/>	<input type="checkbox"/>	<input type="checkbox"/>	10119	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	


Save

If the function: "Switch relay(s) thru I/O" is used, the "Control" function can be used to determine the type of control (edge) of the IO input when switching the relays:


- H level control (is IO high (H) is the relay on, IO = 0 (L) is off.
- LH switching on at rising edge from L (0) to H (1); switch off manually.
- HL switch off on falling edge from H to L; switch on manually.
- TL toggle (switching) with rising edge from L to H.
- TH toggle (switching) on falling edge from H to L.

An unused I/O output can be used as a switch for multiple sockets.


NET-PwrCtrl IO



NET-PwrCtrl HUT (2)



Output: „0“ = 0V; „1“ = 3,3V max. 2 mA
Input: „0“ < 0.4V; „1“ > 2.4V < 12V



Switching

Relay is set for the given time (max 65535 seconds = 18.2h):

when **on**, switched on (relay normally off).

when **off**, switched off (relay normally on).

It is used to control external devices that require a switching pulse. This function has the **highest priority**. All other switching operations (timer, etc.) are switched as an impulse.

Lock: locks the individual sockets/relays for the controll. Button appears gray and can not be clicked.

The name of the socket can be max. 16 characters. Special characters can "confuse" some browsers.

Relay or IO is switched on as long as the key is held down. Two relays or IO's can be used for +/- control (eg dimmer).

After the **restart (power failure)** there is the following switching behaviour for the sockets:

[off] - switch off.

[on] - switch on if necessary with delay [to (s)].

[rs] - restore the last state, if necessary with delay.

The delay can be max. 65535 seconds are what: 1092 minutes or 18.2 hours results

Switching ★

Name /Position/Function NET - Power Control

No.	Name	Lock	Impuls		Hold On	Symbol	at the start:			on when Temp.			Switch on (max. 65535 s = 18.2h)			
			on	off			Time(s)	off	on	rs	after (s)	<		>	28.7°C	
1	Server #1	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	12	<input type="checkbox"/>	10122	<input type="radio"/>	<input type="radio"/>	<input checked="" type="radio"/>	0	<input type="checkbox"/>	<input type="checkbox"/>	22.0	30	<input type="button" value="on"/>
2	Licht	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	3	<input type="checkbox"/>	10123	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	0	<input type="checkbox"/>	<input type="checkbox"/>	22.0	30	<input type="button" value="on"/>
3	Mikroskop	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	3	<input type="checkbox"/>	10124	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	0	<input type="checkbox"/>	<input type="checkbox"/>	22.0	30	<input type="button" value="on"/>
4	Nr.4	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	3	<input checked="" type="checkbox"/>	10125	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	0	<input type="checkbox"/>	<input type="checkbox"/>	22.0	30	<input type="button" value="on"/>
5	Nr.5	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	3	<input type="checkbox"/>	10126	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	0	<input type="checkbox"/>	<input type="checkbox"/>	22.0	30	<input type="button" value="on"/>
6	Nr.6	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	3	<input type="checkbox"/>	10127	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	0	<input type="checkbox"/>	<input type="checkbox"/>	22.0	30	<input type="button" value="off"/>
7	Nr.7	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	3	<input type="checkbox"/>	10128	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	0	<input type="checkbox"/>	<input type="checkbox"/>	22.0	30	<input type="button" value="off"/>
8	Nr.8	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	3	<input type="checkbox"/>	10129	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	0	<input type="checkbox"/>	<input type="checkbox"/>	22.0	30	<input type="button" value="on"/>

Operating distance of the relays with simultaneous switching: (0-255) milliseconds.

since reboot 72 sec. = Day(s) and 00:01:12

Shows elapsed seconds since restart - important for the time delay after startup: It helps to find out how far the power up process has progressed.

The sockets are - for an interval of max. 65535 seconds - on or off. The action taken is indicated in the button and depends on the state of the socket (switched on / off).

Simultaneous switching = only possible via UDP-, URL-Protocol or IO.

Hybrid Relay

This feature is only in HUT3-T

The hybrid circuit supports the relay against high inrush currents when switching on and surges when switching off. A transistor (switched in parallel to the relay) is used for switching on and off as a pulse activates and intercepts the faults.


The advantages of two technologies are combined: high impulse current tolerance of the semiconductor and lossless operation of the relays.

At loads up to 200W can switch the transistor only. In "transistor only" mode up to **300VDC** can be switched, which with a relay is only possible with a lot of effort.

The time resolution is 5 ms. The values are rounded to 5 ms.

Delay cannot be longer as impulse ($T_{Tr-on} > T_{\Delta rel-on}$; $T_{Tr-off} > T_{\Delta rel-off}$).

All values ≤ 200 ms.



No.	Name	Switch with transistor only 200W maximum	T_{Tr-on} (ms) Switch-on pulse	$T_{\Delta rel-on}$ (ms) ON relay delay	T_{Tr-off} (ms) Switch-off pulse	$T_{\Delta rel-off}$ (ms) OFF relay delay
1	R.1	<input type="checkbox"/>	80	40	80	40
2	R.2	<input type="checkbox"/>	80	40	80	40
3	R.3	<input type="checkbox"/>	80	40	80	40
4	R.4	<input type="checkbox"/>	80	40	80	40
5	R.5	<input type="checkbox"/>	80	40	80	40
6	R.6	<input type="checkbox"/>	80	40	80	40
7	R.7	<input type="checkbox"/>	80	40	80	40
8	R.8	<input type="checkbox"/>	80	40	80	40

Wake on LAN

After turning on the relay when "WOL sending" is selected and the delay has elapsed (delayed (1-255 sec.)), ['Wake on LAN'](#) start signal is sent to the network receiver with the MAC (MAC receiver).

The Wake on LAN (in BIOS) option must be enabled in the network receiver.

"Send WOL immediately" button immediately sends the WOL signal regardless of the status of the relay and "Send WOL".

Wake on LAN
★

After switching on the relay/socket when 'Send WOL' selected and the latency (delay) gets the network receiver with the MAC (MAC - receiver) [WOL - Wake on LAN](#) start signal. In the network receiver 'Wake on LAN' must be enabled.

No.	Name	Send WOL	MAC - receiver	delayed (1-255 sec.)	Send WOL immediately
1	Server #1	<input type="checkbox"/>	01:00:00:00:00:00	1	1
2	Licht	<input type="checkbox"/>	00:02:00:00:00:00	1	2
3	Mikroskop	<input type="checkbox"/>	00:00:03:00:00:00	1	3
4	Nr.4	<input type="checkbox"/>	00:00:00:04:00:00	1	4
5	Nr.5	<input type="checkbox"/>	00:00:00:00:05:00	1	5
6	Nr.6	<input type="checkbox"/>	00:00:00:00:00:06	1	6
7	Nr.7	<input type="checkbox"/>	00:00:00:00:00:00	1	7
8	Nr.8	<input type="checkbox"/>	00:00:00:00:00:00	1	8

Timer

They are "plain text timers". Each line is a timer that either turns on or off. Relays and IOs can be switched. There can be a maximum of 30 timers. Semicolon (;) at the beginning means a comment or switches the timer off.

There are four types of timers:

- Weekly timer
- Sunrise/Sunset timer
- One-Shot-Timer
- If-Timer

Relay / IO number = r1-r8; R1-R8; io1-io8; IO1-IO8

Relay / IO Name = name of the relay or IO in " " e.g.: "R.1".

on/off for switching on or off.

Time HH: MM: SS with am / pm optional

Weekdays 1-7 (1 = Sunday, 7 = Saturday) also separated by commas: 1,3,6-7

sr = sunrise

ss = sunset

both optional: +/- HH: MM: SS time **correction**

Date YYYY / MM / DD HH: MM: SS am / pm optional.

Condition: Format:? (!) Relay / IO number / "Name"? = when switched on; ?! when turned off.

Weekly timer

Relay/IO on/off weekdays

r1 on 8:30:01 1-7

Sun timer

Relay/IO on/off ss/sr(+/-correction) weekdays

"IO.8" on sr+00:15:00 1-7

One-shot timer

Relay/IO on/off date

"R.8" on 2019/12/30 08:30:07

If timer

Condition + weekly timer / sun timer / one-shot timer

?r1 io2 off 18:02:00 2,3,5-7

Important !: If the timer should switch immediately after saving (if they are in the switching window), the switching times must be sorted (from early to late; sunrise - sr to sunset - ss) for a specific relay or IO.

If the sorting is reversed, the timers do not switch until the next period (day).

Example:

R2 off 07:35:00 1-7

R2 on 17:00:00 1-7

when saving at 13:20, R2 is switched on immediately.

R2 on 17:00:00 1-7

R2 off 07:35:00 1-7

switched not.

Keepalive Timer

Keepalive Timer:

Sends to the IP a ping [every (min)] and [if there is no echo (no answer)] consecutively - the relay switches off for [shutdown for (sec.)] .

After [continue after (min)], pinging continues. With the "Ping" button the IP can be pinged and tested.

'Switch off for ' = 0: it is only switched off.

'Continue after (min)' = 0: the function does not continue during the overflow.

Max. ping response time = 1000ms.

Shows in which phase
(ping, switch off, wait)
the timer is located.

No.	Send to the IP or Host	a ping	every (minute)	and if no echo x	switch off for (sec.)	continue after (min)	<input checked="" type="checkbox"/> detailed log
1	<input checked="" type="checkbox"/> 192.168.77.27	<input type="button" value="Ping"/>	<input type="text" value="1"/>	<input type="text" value="3"/>	<input type="text" value="60"/>	<input type="text" value="3"/>	<input checked="" type="checkbox"/> time of next ping 13:15
	<input checked="" type="checkbox"/> Switch off relay 0x no echo. All without echo 3						<input type="button" value="Save & Restart"/>
2	<input checked="" type="checkbox"/> anel.eu	<input type="button" value="Ping"/>	<input type="text" value="1"/>	<input type="text" value="3"/>	<input type="text" value="60"/>	<input type="text" value="3"/>	<input checked="" type="checkbox"/> time of next ping 13:14
	<input checked="" type="checkbox"/> Switch off relay Echo received, 0x no echo. All without echo 0						<input type="button" value="Save & Restart"/>
3	<input type="checkbox"/> 0.0.0.0	<input type="button" value="Ping"/>	<input type="text" value="1"/>	<input type="text" value="3"/>	<input type="text" value="60"/>	<input type="text" value="3"/>	<input type="checkbox"/>
	<input type="checkbox"/> Switch off relay						<input type="button" value="Save & Restart"/>
4	<input type="checkbox"/> 0.0.0.0	<input type="button" value="Ping"/>	<input type="text" value="1"/>	<input type="text" value="3"/>	<input type="text" value="60"/>	<input type="text" value="3"/>	<input type="checkbox"/>
	<input type="checkbox"/> Switch off relay						<input type="button" value="Save & Restart"/>
5	<input type="checkbox"/> 0.0.0.0	<input type="button" value="Ping"/>	<input type="text" value="1"/>	<input type="text" value="3"/>	<input type="text" value="60"/>	<input type="text" value="3"/>	<input type="checkbox"/>
	<input type="checkbox"/> Switch off relay						<input type="button" value="Save & Restart"/>
6	<input type="checkbox"/> 0.0.0.0	<input type="button" value="Ping"/>	<input type="text" value="1"/>	<input type="text" value="3"/>	<input type="text" value="60"/>	<input type="text" value="3"/>	<input type="checkbox"/>
	<input type="checkbox"/> Switch off relay						<input type="button" value="Save & Restart"/>
7	<input type="checkbox"/> 0.0.0.0	<input type="button" value="Ping"/>	<input type="text" value="1"/>	<input type="text" value="3"/>	<input type="text" value="60"/>	<input type="text" value="3"/>	<input type="checkbox"/>
	<input type="checkbox"/> Switch off relay						<input type="button" value="Save & Restart"/>
8	<input type="checkbox"/> 0.0.0.0	<input type="button" value="Ping"/>	<input type="text" value="1"/>	<input type="text" value="3"/>	<input type="text" value="60"/>	<input type="text" value="3"/>	<input type="checkbox"/>
	<input type="checkbox"/> Switch off relay						<input type="button" value="Save & Restart"/>
Nr:7 sek:50 min:4 IP=85.13.162.218		<input type="button" value="Test"/>	<input type="text" value="1-15 minutes"/>	<input type="text" value="1-15"/>	<input type="text" value="1-255 sec
0=only off"/>	<input type="text" value="1-255 min
0=stop"/>	



Sensors

This function only HUT(2,3)

- External sensor for the Net-PwrCtrl - HUT & IO.
- Temperature, humidity & brightness with high accuracy.
- 5 settings per parameter.
- Connection (simple and cost-effective) via ethernet cable including power.
- Adjustable hysteresis.
- All relays controllable.
- Adapter for HUT / HUT2
- DIN rail and 'wall' mounting.



Measurement:	Temperature	Humidity	Brightness
Sensor IC	SHT21	SHT21	BH1750FVI
Operating Range	-40 - +125 °C	0 - 100 %RH	0 - 65535 lx
Resolution	0.01 °C	0.04 %RH	1 lx
Accuracy tolerance	±0.3 °C	±2.0 %RH	1.2
Repeatability	±0.1 °C	±0.1 %RH	1 lx



Configuration Backup

The saved configuration file can be used to configure multiple NET PwrCtrl with the same settings. Since the host name of the device needs to be changed (must be unique on the network) after the change is best:

- Close browser (all windows).
- Start the browser and call NET-PwrCtrl with the new host name.

Click on 'Save configuration' download ,net-pwrctrl.cfg'.

Excerpt:

```
// NET-PWRCTRL_06.4
// This file can be shortened line by line.
// Keywords before ':' must not be changed.
// In the {...} area, '1' may occur only once.
// (R) is read only (will be not changed).
```

```
//-----[Lan]-----
Hostname: NET-CONTROL1
DHCP: 1
IP: 192.168.2.109
Gateway: 192.168.2.1
Mask: 255.255.255.0
First DNS: 192.168.2.1
Secound DNS: 0.0.0.0
```

...

To get special characters please use a UTF-8 capable editor (eg Notepad ++).
Depending on the language version, the keywords in the net-pwrctrl.cfg file change.
The files of the other language can not be used.

Attention! When restoring, the existing configuration is deleted.
NET-PwrCtrl restarts.

Save configuration.

Download the configuration file. It can be used to configure multiple devices with the same settings. The hostname and IP (DHCP off) must be unique and changed.

The configuration file is saved under the name 'net-pwrctrl.cfg'.
If the browser displays a warning: **The file is harmless.**

The file has UTF-8 format: important for using the special characters in the names. Should therefore be edited with a UTF-8 capable editor (such as Notepad ++).

Save configuration.

Restore Configuration.

The configuration file can be opened, changed and sent to the device here.
Can be edited by clicking in the window.
After the change, the file must be tested by clicking on the 'Test' button.

The (changed) configuration file:

Datei auswählen Keine ausgewählt

The new settings are applied after the file has been sent. The device will restart. This tab can be closed.

If the **host name** is changed: close the browser and call NET-PwrCtrl with the new host name.
If the **IP** is changed: close the browser and call NET-PwrCtrl with the new IP or hostname.
If the **port number** has changed: close the browser and call NET-PwrCtrl with the new IP or hostname +: portnumber (for example: net-control:85).

API interfaces

Please use the description from our forum :

[UDP - Control](#)

For control from the software via UDP socket.

<https://forum.anel.eu/viewtopic.php?f=16&t=207&sid=98b504e8d840396fe5cb098faf560b51>

[URL - Control](#)

For the control from the address bar of the browser.

<https://forum.anel.eu/viewtopic.php?f=52&t=888&sid=98b504e8d840396fe5cb098faf560b51>

[Windows .bat / cmd - Control](#)

Tool for controlling all NET-PwrCtrl from the windows command prompt/.bat file/own software.

<https://forum.anel.eu/viewtopic.php?f=59&t=994&sid=98b504e8d840396fe5cb098faf560b51>

Access from the Internet

If NET-PwrCtrl should be controlled from the Internet (via DSL access), the router must be set accordingly: The router's port forwarding must be set to the IP and port of the NET-PwrCtrl. NET-PwrCtrl can then be called from the Internet using the router's **Internet IP address** (DSL-address **not** 192.168.x.x). Hostname can only be used internally.

If there are several devices, the port address of the NET-PwrCtrl must be changed (e.g. to 81). Port forwarding must be set accordingly. Each NET-PwrCtrl must have a different port number. With the Internet-IP-address:Port can be called. (<http://46.88.135.21:81>)

Below: example of setting.

NET-IO-HUT-TEST

delete

Name of the redirection

NET-IO-HUT-TEST

Applies to the following device

NET-IO-HUT-TEST

Use template

Web-Server

Ports to redirect

What is that?

TCP

83

-

▶

83

-

TCP

80

-

▶

83

-

+ Create other TCP redirection

Another possibility: [ngrok](#). A (small) server allows access from the Internet without port forwarding and via https: (SSL). It requires registration but is free for only one HTTP/TCP tunnel (stand 08.2018).

Call: `ngrok.exe http <your ip>:<your port> region=eu`
then <http://localhost:4040> in the browser for the address.

```

C:\Users\andy\Desktop\ngrok.exe
ngrok by @inconshreveable (Ctrl+C to quit)

Session Status
Account      online
Version     2.2.8
Region      Europe (eu)
Web Interface http://127.0.0.1:4040
Forwarding   http://7f0cf0af.eu.ngrok.io -> 192.168.2.113:80
             https://7f0cf0af.eu.ngrok.io -> 192.168.2.113:80

Connections      ttl    opn    rt1    rt5    p50    p90
                  655    0      1.99   1.39   0.04   0.05

HTTP Requests
-----
GET /kal.cfg      200 OK
GET /daten.cfg   200 OK
GET /kal.cfg      200 OK
GET /daten.cfg   200 OK
GET /kal.cfg      200 OK
GET /daten.cfg   200 OK
GET /kal.cfg      200 OK
GET /daten.cfg   200 OK
GET /kal.cfg      200 OK
GET /daten.cfg   200 OK

```